

# iPhone 4 Headphone Jack & Volume Control Cable Replacement

## INTRODUCTION

A new headphone jack will also give you new electronic portions of the silent switch and volume buttons.



### TOOLS:

- [iPhone 5-Point Pentalobe Screwdriver](#) (1)  
*(if iPhone has external pentalobe screws)*
- [iPhone SIM Card Eject Tool](#) (1)
- [Phillips #000 Screwdriver](#) (1)  
*(if iPhone has external Phillips screws)*
- [Phillips #00 Screwdriver](#) (1)
- [Plastic Opening Tools](#) (1)
- [2.5 mm Flathead Screwdriver](#) (1)
- [Spudger](#) (1)
- [Tweezers](#) (1)






### PARTS:

- [iPhone 4 Headphone Jack & Volume Control Cable](#) (1)

## Step 1 — Rear Panel



- Before disassembling your iPhone, be sure it is powered off. 
- Your iPhone 4 rear cover may have either two #000 Phillips screws or Apple's 5-Point "Pentalobe" screws ([second image](#)). Check which screws you have, and ensure you also have the correct screwdriver in order to remove them.
- Remove the two 3.6 mm Pentalobe or Phillips #000 screws next to the dock connector.
- During reassembly, we recommend you replace the 5-point screws with equivalent Phillips screws. 
- The 5-Point Screwdriver should only be used once, as it has the potential to strip the screws. 

## Step 2





- Push the rear panel toward the top edge of the iPhone.
- The panel will move about 2 mm.



## Step 3



- Pinch the rear panel with your fingers and lift it away from the iPhone. Alternatively, use a [Small Suction Cup](#).
- Be careful not to damage the plastic clips attached to the rear panel. 
- If you are installing a new rear panel, be sure to remove the plastic protective sticker from the inside of the camera lens and the sticker from the large black area near the lens. 

## Step 4 — Battery



- Remove the single 2.5 mm Phillips screw securing the battery connector to the logic board.
- Some devices may have two screws, one of which holds down the contact pad which is located above the screw indicated in red in the photo.



## Step 5



- Use a plastic opening tool to gently pry the battery connector up from its socket on the logic board.
- Be very careful to only pry up on the battery connector and not the socket on the logic board. If you pry up on the logic board socket, you may break it entirely.
- Remove the metal clip covering the antenna connector.



## Step 6



- Use the clear plastic pull tab to gently lift the battery out of the iPhone.
- Do not remove the plastic tab from the iPhone.
- You may need to use a plastic opening tool to loosen the adhesive under the battery.
- Remove the contact clip from the iPhone.
- Before reconnecting the battery connector, be sure the pressure contact (shown in red) is properly positioned next to the battery connector.
- Before reassembly, be sure to clean all metal-to-metal contact points on the pressure contact as well as its contact point on the rear panel with a de-greaser such as windex. The oils on your fingers have the potential to cause wireless interference issues.





## Step 7 — Logic Board



- Use a SIM card eject tool or a paperclip to eject the SIM card and its holder.
- This may require a significant amount of force.
- Remove the SIM card and its holder.




## Step 8



- Remove the following two screws:
  - One 1.2 mm Phillips
  - One 1.6 mm Phillips
- Remove the thin steel dock connector cable cover from the iPhone.
- Before reassembly, be sure to clean all metal-to-metal contact points on the dock connector cable cover with a de-greaser such as windex. The oils on your fingers have the potential to cause wireless interference issues.




## Step 9



●

## Step 10



- Carefully peel the dock ribbon cable off the logic board and the lower speaker enclosure.
- Do not use excessive force to peel the dock ribbon cable off the logic board. Doing so may tear the cable.




## Step 11



- Use an iPod opening tool to pry the lower antenna connector up off its socket on the logic board.






## Step 12



- Remove the 1.9 mm Phillips screw securing the bottom of the logic board to the inner case.

## Step 13



- Remove the following five screws securing the Wi-Fi antenna to the logic board:
  - One 2.3 mm Phillips
  - Two 1.6 mm Phillips
  - One 1.4 mm Phillips
  - One 4.8 mm Phillips
- When re-assembling, start off with replacing the 4.8 mm Philips screw first, then the 2.3 mm. *This is to ensure there is no mix-up, and avoid rendering the LCD and digitizer useless.* 
- Also make sure to put the long 4.8 mm Philips back in correctly when reassembling. This is the ground for the Wi-Fi antenna and is often the culprit if you are having bad Wi-Fi reception after reassembly. 


## Step 14



- Use an iPod opening tool to slightly lift the top edge of the Wi-Fi antenna away from the logic board.
- Use the tip of a spudger to pull the Wi-Fi retaining clips away from the inner frame.
- Remove the Wi-Fi antenna from the iPhone. Make sure you don't lose the metal clips on the top of the cover where the 4.8mm screw attaches or the 4.8mm screw. That's the primary reason for abnormal Wi-Fi performance after the reassembly.
- Before reassembly, be sure to clean all metal-to-metal contact points on the connector cover with a de-greaser such as Windex. The oils on your fingers have the potential to cause wireless interference issues. **Do not** clean the connectors themselves with Windex.




## Step 15



- Use an iPod opening tool to carefully lift the rear camera connector up off its socket on the logic board.
- Remove the rear camera.

## Step 16



- Remove the small circular white sticker (warranty sticker and water indicator) covering the screw near the battery pull tab.
- Remove the 2.4 mm Phillips screw that was hidden underneath the sticker.



## Step 17



- Use the edge of a plastic opening tool to gently pry the following connectors up and out of their sockets on the logic board:
  - Digitizer cable (pry from bottom)
  - LCD cable (pry from bottom)
  - Headphone jack/volume button cable (pry from top)
  - Top Microphone/sleep button cable (pry from top)
  - Front camera cable (pry from top)

## Step 18





- Use a small flathead screwdriver to remove the 4.8 mm standoff near the headphone jack.
- When reassembling the device, this standoff sets the height of the Wi-Fi shield removed in step 13. If not torqued down, the shield will be above the plane of the frame and the back will not slide into place in step 2. The shield should be flush with the headphone jack.
- When reassembling the motherboard, ensure that its edge sits under the circled standoff, otherwise the screws will not fit.
- When reassembling ensure that the small rubber spacer attached to the top of the motherboard is in place. Without this part the motherboard could damage the ribbon cables around it.




## Step 19



- Carefully remove the logic board from the iPhone, minding any cables that may get caught.
- Be careful not to damage the small gold prong (marked in red, near the top) as it's very fragile. 
- On reassembly, be careful not to trap the lower antenna cable beneath the logic board. 

## Step 20 — Front Facing Camera



- Use the edge of an iPod opening tool to lift the thin steel front camera retainer off the front camera.
- Remove the front camera retainer.



## Step 21



- Carefully lift the front facing camera out of the iPhone.
- It may be helpful to use tweezers to reinstall the front camera retainer.




## Step 22 — Headphone Jack & Volume Control Cable



- Remove the following two screws securing the vibrator to the inner frame:
  - One 6 mm Phillips screw
  - One 1.4 mm Phillips screw
- Remove the vibrator from the inner case.




## Step 23



- Use the edge of a plastic opening tool to peel the small strip of black tape off the back of the volume button bracket.
- Peel the tape starting from the side nearest the top of the phone.
- Carefully remove the remaining portion of tape off the small section of ribbon cable near the inside of the bottom volume button.




## Step 24



- Remove the five Phillips screws securing the silent and volume button brackets to the outer case.
- The screw directly below the silent switch is shorter than the others.
- The left screw securing the volume control bracket is longer than the rest.


## Step 25



- Use a pair of tweezers to carefully pull the silent switch and its bracket from the side of the outer case.
- Don't try to completely remove the silent switch just yet.





## Step 26



- Grab the headphone jack with a pair of tweezers and remove the assembly from the iPhone, being careful not to rip the thin ribbon cables.

## Step 27



- If you are not replacing the headphone jack assembly with a new unit, skip this step. 
- Use the edge of a plastic opening tool to peel the electronic portion of the silent switch off its metal bracket.
- Transfer the bracket to the new silent switch.
- Repeat this procedure to peel the metal volume button bracket off the electronic portion of the volume buttons.
- Transfer the volume button bracket to the new volume buttons.

---

To reassemble your device, follow these instructions in reverse order.